

Tabelle1

DIP-Schalter Eingangswiderstand MC-Systeme								
Position	1	2	3	4	5	6	7	8
Ohm	10	24	47	100	240	470	820	1000
5,4	ON	ON	ON	ON	ON	ON	ON	ON
5,5	ON	ON	ON	ON	ON	OFF	OFF	ON
5,7	ON	ON	ON	OFF	ON	ON	ON	ON
5,9	ON	ON	ON	OFF	OFF	ON	OFF	ON
6	ON	ON	ON	OFF	OFF	OFF	OFF	OFF
6,5	ON	ON	OFF	OFF	ON	ON	ON	ON
7,3	ON	ON	OFF	OFF	OFF	OFF	OFF	OFF
7,5	ON	OFF	ON	ON	OFF	ON	OFF	OFF
8	ON	OFF	ON	OFF	ON	OFF	OFF	OFF
8,5	ON	OFF	OFF	ON	ON	ON	ON	OFF
9	ON	OFF	OFF	ON	OFF	OFF	OFF	ON
9,5	ON	OFF	OFF	OFF	ON	OFF	ON	OFF
10	ON	OFF	OFF	OFF	OFF	OFF	OFF	OFF
12,5	OFF	ON	ON	ON	OFF	ON	ON	OFF
15	OFF	ON	ON	OFF	OFF	OFF	OFF	OFF
17,6	OFF	ON	OFF	ON	OFF	OFF	ON	OFF
20,1	OFF	ON	OFF	OFF	OFF	ON	ON	ON
25,3	OFF	OFF	ON	ON	ON	ON	ON	ON
30	OFF	OFF	ON	ON	OFF	ON	OFF	OFF
36,5	OFF	OFF	ON	OFF	ON	ON	OFF	OFF
40,7	OFF	OFF	ON	OFF	OFF	ON	ON	OFF
47	OFF	OFF	ON	OFF	OFF	OFF	OFF	OFF
58,4	OFF	OFF	OFF	ON	ON	ON	OFF	ON
62	OFF	OFF	OFF	ON	ON	ON	OFF	OFF
70	OFF	OFF	OFF	ON	OFF	ON	ON	ON
75,1	OFF	OFF	OFF	ON	OFF	ON	ON	OFF
82	OFF	OFF	OFF	ON	OFF	OFF	ON	ON
90,9	OFF	OFF	OFF	ON	OFF	OFF	OFF	ON
100	OFF	OFF	OFF	ON	OFF	OFF	OFF	OFF
120	OFF	OFF	OFF	OFF	ON	ON	ON	ON
136	OFF	OFF	OFF	OFF	ON	ON	ON	OFF
140	OFF	OFF	OFF	OFF	ON	ON	OFF	ON
160	OFF	OFF	OFF	OFF	ON	OFF	ON	ON
163,5	OFF	OFF	OFF	OFF	ON	ON	OFF	OFF
191	OFF	OFF	OFF	OFF	ON	OFF	ON	OFF
200	OFF	OFF	OFF	OFF	ON	OFF	OFF	ON
232	OFF	OFF	OFF	OFF	OFF	ON	ON	ON
249	OFF	OFF	OFF	OFF	ON	OFF	OFF	OFF
301	OFF	OFF	OFF	OFF	OFF	ON	ON	OFF
322	OFF	OFF	OFF	OFF	OFF	ON	OFF	ON
452	OFF	OFF	OFF	OFF	OFF	OFF	ON	ON
470	OFF	OFF	OFF	OFF	OFF	ON	OFF	OFF
820	OFF	OFF	OFF	OFF	OFF	OFF	ON	OFF
1000	OFF	OFF	OFF	OFF	OFF	OFF	OFF	ON
47000	OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF

Tabelle1

DIP-Schalter Eingangskapazität MM-Systeme

Position	1	2	3	4
Picofarad	50	100	180	330
50	ON	OFF	OFF	OFF
100	OFF	ON	OFF	OFF
150	ON	ON	OFF	OFF
180	OFF	OFF	ON	OFF
230	ON	OFF	ON	OFF
280	OFF	ON	ON	OFF
330	OFF	OFF	OFF	ON
380	ON	OFF	OFF	ON
430	OFF	ON	OFF	ON
480	ON	ON	OFF	ON
510	OFF	OFF	ON	ON
560	ON	OFF	ON	ON
610	OFF	ON	ON	ON
660	ON	ON	ON	ON

Bitte hier noch die Kapazität des Tonarmkabels und des Verbindungskabels dazu rechnen. Falls unbekannt: Tonarm-Kabel bei guten Kabeln 50pf bis 70pf pro Meter